

# Flipping chan\_sip/PJSIP default protocol

This page reorganizes the operational steps for **Flipping chan\_sip/PJSIP default protocol**.

You may want to use the PJSIP protocol as default protocol on port 5060 for your endpoints. You need to remember the server to server and the server internal calls must still be run over chan\_sip protocol. These are the changes to apply:

in pjsip.conf change the port from 5080 to 5060, 5081 to 5061 and so on, based on the protocols you are using

in sip.conf set the "bindport" to 5080 in the [general] section. Set the port parameter "port=5080" in the [pbx] sections

Restart asterisk

## Current Verification

After applying the change, verify the related MiRTA PBX page, the Asterisk logs, and the relevant Status menu entry. Recheck tenant selection before testing tenant-specific behavior.

---

Revision #3

Created 2026-06-02 21:59:24 UTC by Admin

Updated 2026-06-02 22:00:22 UTC by Admin