

Digium D40/D45 - MAC request

[Back to Phone Model Examples](#)

```
<?xml version="1.0" ?>
<config>
  <setting id="login_password" value="{ $adminpw|222222}" />
  <setting id="time_zone" value="America/New_York" />
  <setting id="time_source" value="ntp" />
  <setting id="ntp_server" value="0.us.pool.ntp.org" />
  <setting id="ntp_resync" value="86400" />
  <setting id="enable_blf_on_unused_line_keys" value="0" />
  <setting id="blf_contact_group" value="Default" />
  <setting id="logo_file" value="user" path="/user_image.png"
url="http://pbx.somecompnay.com/pbx/autoprovision/{ $provisioning_password}/logo_digium_d40"/>
  <setting id="accept_local_calls" value="host" />
  <setting id="transport_udp_enabled" value="1" />
  <setting id="transport_udp_port" value="5060" />
  <setting id="transport_tcp_enabled" value="1" />
  <setting id="transport_tcp_port" value="5060" />
  <setting id="display_mc_notification" value="{ $missed_call_log|0|select|No=0,Yes=1}" />
  <setting id="brightness" value="10" />
  <setting id="contrast" value="10" />
  <setting id="dim_backlight" value="1" />
  <setting id="backlight_timeout" value="30" />
  <setting id="backlight_dim_level" value="2" />
  <setting id="ringer_volume" value="5" />
  <setting id="speaker_volume" value="5" />
  <setting id="handset_volume" value="5" />
  <setting id="headset_volume" value="5" />
  <setting id="reset_call_volume" value="0" />
  <setting id="default_ringtone" value="Digium" />
  <setting id="active_ringtone" value="Digium" />
  <setting id="headset_answer" value="0" />
```

```
<setting id="desi_strip_enable" value="1" />
<setting id="name_format" value="first_last" />
<setting id="contacts_max_subscriptions" value="10" />
<setting id="blf_contact_group" value="Default" />
<setting id="network_enable_dhcp" value="1" />
<setting id="network_static_ip_address" value="" />
<setting id="network_subnet_mask" value="" />
<setting id="network_default_gateway" value="" />
<setting id="network_domain_name" value="" />
<setting id="network_primary_dns_server" value="" />
<setting id="network_secondary_dns_server" value="" />
<setting id="network_vlan_discovery_mode" value="NONE" network="10.10.0.0/16" />
<setting id="sip_qos" value="0" />
<setting id="rtp_qos" value="0" />
<setting id="pc_qos" value="0" />
<setting id="network_vlan_id" value="44" />
<setting id="log_level" value="debug" />
<setting id="enable_logging" value="0" />
<setting id="log_server" value="10.1.2.3" />
<setting id="log_port" value="514" />
<setting id="web_ui_enabled" value="{ $webinterface|0|select|No=0,Yes=1}" />
<setting id="sip_dscp" value="24" />
<setting id="rtp_dscp" value="46" />
<setting id="udp_ka_interval" value="60" />
<setting id="enable_check_sync" value="1" />
<setting id="locale" value="en_US" />
<setting id="ehs" value="auto" />
<setting id="enable_check_sync" value="1" />
<MiscSettings>
</MiscSettings>
<codecs>
  <codec id="PCMU" priority="255" packetization="20" jitter_min="0" jitter_max="0"
jitter_target="0" enabled="1" />
  <codec id="PCMA" priority="13" packetization="20" jitter_min="0" jitter_max="0"
jitter_target="0" enabled="1" />
  <codec id="G722" priority="11" packetization="20" jitter_min="0" jitter_max="0"
jitter_target="0" enabled="1" />
  <codec id="G726-32" priority="7" packetization="20" jitter_min="0" jitter_max="0"
jitter_target="0" enabled="1" />
  <codec id="G729" priority="4" packetization="20" jitter_min="0" jitter_max="0"
jitter_target="0" enabled="1" />
```

```
<codec id="L16" priority="2" packetization="20" jitter_min="0" jitter_max="0"
jitter_target="0" enabled="1" />
<codec id="L16-256" priority="1" packetization="20" jitter_min="0" jitter_max="0"
jitter_target="0" enabled="1" />
</codecs>
<contacts url="http://pbx.somecompany.com/pbx/autoprovision/{$_provisioning_password}/{$_mac}-
directory.xml" id="internal" />
<smart_blf>
</smart_blf>
<firmwares>
  <firmware model="D50" version="2_0_2_0_78957"
url="http://pbx.somecompany.com/pbx/autoprovision/{$_provisioning_password}/DigiumD50" />
  <firmware model="D70" version="2_0_2_0_78957"
url="http://pbx.somecompany.com/pbx/autoprovision/{$_provisioning_password}/DigiumD70" />
  <firmware model="D40" version="2_0_2_0_78957"
url="http://pbx.somecompany.com/pbx/autoprovision/{$_provisioning_password}/DigiumD40" />
  <firmware model="D45" version="2_0_2_0_78957"
url="http://pbx.somecompany.com/pbx/autoprovision/{$_provisioning_password}/DigiumD45" />
</firmwares>
<ringtones>
<tones>
  <tone id="Alarm" display="Alarm" type="phone" />
  <tone id="Chimes" display="Chimes" type="phone" />
  <tone id="Digium" display="Digium" type="phone" />
  <tone id="GuitarStrum" display="Guitar Strum" type="phone" />
  <tone id="Jingle" display="Jingle" type="phone" />
  <tone id="Office" display="Office" type="phone" />
  <tone id="Office2" display="Office 2" type="phone" />
  <tone id="RotaryPhone" display="Rotary Phone" type="phone" />
  <tone id="SteelDrum" display="Steel Drum" type="phone" />
  <tone id="Techno" display="Techno" type="phone" />
  <tone id="Theme" display="Theme" type="phone" />
  <tone id="Tweedle" display="Tweedle" type="phone" />
  <tone id="Twinkle" display="Twinkle" type="phone" />
  <tone id="Vibe" display="Vibe" type="phone" />
</tones>
<alerts>
  <alert alert_info="normal" ringtone_id="Digium" ring_type="normal" />
  <alert alert_info="ring-answer" ringtone_id="Digium" ring_type="ring-answer" />
<alert alert_info="intercom" ringtone_id="" ring_type="answer" />
  <alert alert_info="visual" ringtone_id="" ring_type="visual" />
```

```
</alerts>
</ringtones>
<accounts>
  {line_loop}
    <account
      index="{${line_m1}}"
      status="{${line_active}}"
      register="1"
      account_id="{${line}}"
      username="{${authname}}"
      authname="{${authname}}"
      password="{${secret}}"
      passcode="{${secret}}"
      line_label="{${displayname}}"
      caller_id="{${username}}"
      voicemail = *97
      dial_plan="911|011xxxx.T3|1xxxxxxxxxx|[2-9]xxxxxxxxxx|*xx.T3|**xx.T3"
      visual_voicemail="0"
      outbound_proxy=""
      outbound_port=""
      conflict="replace"
    >
      <host_primary
        server="pbx.somecompany.com"
        port="5060"
        transport="udp"
        reregister="300"
        retry="25"
        num_retries="5"
      />
    </account>
  {/line_loop}
</accounts>
</config>
```

Revision #1

Created 2026-09-22 09:31:45 UTC by Admin

Updated 2026-09-22 09:31:45 UTC by Admin