

Yealink v.72

[Back to Phone Model Examples](#)

```
#!/version:1.0.0.1
##File header "#!/version:1.0.0.1" can not be edited or deleted, and must be placed in the
first line.##

#####
##                                Accounts                                ##
#####

{line_loop}
account.${line_m1}.enable = ${line_active}
account.${line_m1}.label = ${number}
account.${line_m1}.display_name = ${displayname}
account.${line_m1}.auth_name = ${username}
account.${line_m1}.user_name = ${authname}
account.${line_m1}.password = ${secret}
account.${line_m1}.sip_server.1.address = ${server_host}
account.${line_m1}.sip_server.1.port = ${server_port}
account.${line_m1}.sip_server.1.expires = 300
account.${line_m1}.unregister_on_reboot = 1
account.${line_m1}.outbound_proxy_enable = 1
account.${line_m1}.outbound_host = ${server_host}
account.${line_m1}.outbound_port = ${server_port}
{/line_loop}

#####
##                                Line Keys                                ##
#####

{loop_linekey1}
linekey.${key}.type = ${type}
linekey.${key}.line = ${account}
linekey.${key}.value = ${extension}
linekey.${key}.pickup_value = ${parameter}
linekey.${key}.label = ${label}
```

```
{/loop_linekey1}
```

```
#####
```

```
##                                Memory Keys                                ##
```

```
#####
```

```
{loop_memkey1}
```

```
memorykey.{ $key }.type = { $type }
```

```
memorykey.{ $key }.line = { $account }
```

```
memorykey.{ $key }.value = { $extension }
```

```
memorykey.{ $key }.pickup_value = { $parameter }
```

```
{/loop_memkey1}
```

```
#####
```

```
##                                Network                                ##
```

```
#####
```

```
network.pc_port.enable = 1
```

```
network.bridge_mode = 1
```

```
#!version:1.0.0.1
```

```
##File header "#!version:1.0.0.1" can not be edited or deleted, and must be placed in the  
first line.##
```

```
#####
```

```
##                                Time Settings                                ##
```

```
#####
```

```
#local_time.time_zone = +2
```

```
#local_time.time_zone_name = Latvia(Riga)
```

```
#local_time.ntp_server1 = lt.pool.ntp.org
```

```
#local_time.ntp_server2 = cn.pool.ntp.org
```

```
#####
```

```
##                                Phone Features                                ##
```

```
#####
```

```
#Configure the logo mode of the LCD screen; 0-Disabled (default), 1-System logo, 2-Custom  
logo;
```

```
phone_setting.lcd_logo.mode = 0
```

```
#####  
##          Configure the access URL of firmware          ##  
#####  
  
#firmware.url = http://.../provisioning/SIP-T26P/6.72.0.80.rom  
  
#####  
##          Auto Provisioning          ##  
#####  
  
auto_provision.power_on = 1  
auto_provision.repeat.enable = 1  
auto_provision.repeat.minutes = 60  
auto_provision.dhcp_option.enable = 0
```

Revision #1

Created 2026-09-22 09:31:44 UTC by Admin

Updated 2026-09-22 09:31:44 UTC by Admin